# KBPC10005~KBPC1010

# SINGLE-PHASE SILICON BRIDGE RECTIFIERS

**REVERSE VOLTAGE: 50 V to 1000 V** 

**FORWARD CURRENT: 10 A** 


#### **Features**

- Reliable low cost construction
- · Ideal for printed circuit board
- · Low forward voltage drop
- · Low reverse leakage current
- · High surge current capability

# **Mechanical Data**

· Case: KBPC

## **KBPC**



Dimensions in inches and (millimeters)

# **Absolute Maximum Ratings and Characteristics**

Rating at 25 °C ambient temperature unless otherwise specified. Single phase, half wave, 60 Hz, resistive or inductive load. For capacitive load, derate current by 20%

Symbol	KBPC	KBPC	KBPC	KBPC	KBPC	KBPC	KBPC	Units
$V_{RRM}$	50	100	200	400	600	800	1000	V
$V_{RMS}$	35	70	140	280	420	560	700	V
$V_{DC}$	50	100	200	400	600	800	1000	V
I <sub>(AV)</sub>	10							Α
I <sub>FSM</sub>	200						Α	
V <sub>F</sub>	1.2						V	
I <sub>R</sub>	10 500						μΑ	
CJ	200						pF	
$R_{\theta JA}$	25						°C/W	
$R_{\theta JC}$	5						°C/W	
$T_J,T_S$	- 55 to + 125							°C
	$\begin{array}{c} V_{RRM} \\ V_{RMS} \\ V_{DC} \\ I_{(AV)} \\ I_{FSM} \\ V_{F} \\ I_{R} \\ C_{J} \\ R_{\theta JA} \\ R_{\theta JC} \\ \end{array}$	Symbol   10005   VRRM   50   VRMS   35   VDC   50   I(AV)   IFSM   VF   IR   CJ   ReJA   ReJC   ReJC   Red   Red	Symbol 10005 1001   V <sub>RRM</sub> 50 100   V <sub>RMS</sub> 35 70   V <sub>DC</sub> 50 100   I <sub>(AV)</sub> I <sub>FSM</sub> V <sub>F</sub> I <sub>R</sub> C <sub>J</sub> R <sub>θJA</sub> R <sub>θJC</sub> R <sub>θJC</sub>	Symbol 10005 1001 1002   V <sub>RRM</sub> 50 100 200   V <sub>RMS</sub> 35 70 140   V <sub>DC</sub> 50 100 200   I <sub>(AV)</sub> I <sub>FSM</sub> V <sub>F</sub> I <sub>R</sub> C <sub>J</sub> R <sub>θJA</sub> R <sub>θJC</sub>	Symbol 10005 1001 1002 1004   V <sub>RRM</sub> 50 100 200 400   V <sub>RMS</sub> 35 70 140 280   V <sub>DC</sub> 50 100 200 400   I <sub>(AV)</sub> 10 200   V <sub>F</sub> 1.2 10   I <sub>R</sub> 10 500   C <sub>J</sub> 200 200   R <sub>θJA</sub> 25 5	Symbol 10005 1001 1002 1004 1006   V <sub>RRM</sub> 50 100 200 400 600   V <sub>RMS</sub> 35 70 140 280 420   V <sub>DC</sub> 50 100 200 400 600   I <sub>(AV)</sub> 10 200   V <sub>F</sub> 1.2 10 500   C <sub>J</sub> 200 200 200   R <sub>θJA</sub> 25 5	Symbol 10005 1001 1002 1004 1006 1008   V <sub>RRM</sub> 50 100 200 400 600 800   V <sub>RMS</sub> 35 70 140 280 420 560   V <sub>DC</sub> 50 100 200 400 600 800   I <sub>(AV)</sub> 10 200 400 600 800   V <sub>F</sub> 1.2 10 500 500 1.2   I <sub>R</sub> 10 500 200 200 200 R <sub>θJA</sub> 25   R <sub>θJC</sub> 5 5 5 5 5 6 600 800	Symbol 10005 1001 1002 1004 1006 1008 1010   V <sub>RRM</sub> 50 100 200 400 600 800 1000   V <sub>RMS</sub> 35 70 140 280 420 560 700   V <sub>DC</sub> 50 100 200 400 600 800 1000   I <sub>(AV)</sub> 10 200 400 600 800 1000   V <sub>F</sub> 1.2 10 500 500 500 700   C <sub>J</sub> 200 200 200 700 <

<sup>1)</sup> Measured at 1 MHz and applied reverse voltage of 4 VDC.



# SEMTECH ELECTRONICS LTD.

(Subsidiary of Semtech International Holdings Limited, a company listed on the Hong Kong Stock Exchange, Stock Code: 724)









Dated: 16/07/2006 H


 $<sup>^{2)}</sup>$  Unit mounted on 8.6 X 8.6 X 0.24" thick (22 X 22 X 0.6 cm) Al, Plate.


<sup>&</sup>lt;sup>3)</sup> Unit mounted on P.C.B. at 0.375" (9.5 mm) lead length with 0.5 x 0.5" (12 x 12 mm) copper pads.

### RATINGS AND CHARACTERISTIC CURVES









(Subsidiary of Semtech International Holdings Limited, a company listed on the Hong Kong Stock Exchange, Stock Code: 724)







| CERTIFICATION | CERTIFICATIO