

## NTE7120 Integrated Circuit 3 Channel Video Amp for High Resolution Color TV

**Description:**

The NTE7120 is a semiconductor integrated circuit in a 30-Lead DIP type package that has a built-in 3-channel amplifier with 50MHz band. Every channel is provided with a broad-band amplifier, main/sub contrast control, main/sub luminance (brightness) control, peaking, blanking, and peak limiter functions. Accordingly, this device is designed for use in high-resolution color display monitors.

**Features:**

- The employment of a new bi-polar wafer process makes it possible to reduce power dissipation, and 3 channels can be incorporated in this amplifier ( $V_{CC} = 12V$ ,  $I_{CC} = 77mA$ )
- Input:  $1V_{P-P}$  (Typical)  
 Output:  $V_{P-P}$  (Maximum)  
 Frequency Band: 50MHz
- Main and sub contrast and luminance controls are provided; the main control can change contrast and luminance at the same time for 3 channels, and the sub control can change them independently for each channel.
- The DC feedback circuit built in the IC can produce a stable DC level at the IC output pins.

**Applications:**

- CRT Display

**Absolute Maximum Ratings:**

Supply Voltage,  $V_{CC}$  ..... 14V  
 Power Dissipation,  $P_D$  ..... 1670mW  
 Operating Temperature Range,  $T_{opr}$  .....  $-20^{\circ}$  to  $+65^{\circ}C$   
 Storage Temperature Range,  $T_{stg}$  .....  $-40^{\circ}$  to  $+125^{\circ}C$

**Recommended Operating Conditions:**

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Supply Voltage Range	$V_{CC}$		11.0	–	12.5	V
Rated Supply Voltage	$V_{CC}$		0	12	–	V

### Pin Connection Diagram

N.C.	<b>1</b>	<b>30</b>	White Peak
V <sub>CC</sub> (R)	<b>2</b>	<b>29</b>	R Out
R In	<b>3</b>	<b>28</b>	R Hold
R Sub Contrast	<b>4</b>	<b>27</b>	R Sub BRT
R Peaking	<b>5</b>	<b>26</b>	GND (R)
V <sub>CC</sub>	<b>6</b>	<b>25</b>	G Out
G In	<b>7</b>	<b>24</b>	G Hold
G Sub Contrast	<b>8</b>	<b>23</b>	G Sub BRT
G Peaking	<b>9</b>	<b>22</b>	GND (G)
V <sub>CC</sub> (B)	<b>10</b>	<b>21</b>	B Out
B In	<b>11</b>	<b>20</b>	B Hold
B Sub Contrast	<b>12</b>	<b>19</b>	B Sub Bright
B Peaking	<b>13</b>	<b>18</b>	GND (B)
Contrast	<b>14</b>	<b>17</b>	Blanking Pulse
Clamp Pulse	<b>15</b>	<b>16</b>	Brightness

