Unit: mm


TOSHIBA Transistor Silicon PNP Epitaxial Type (PCT Process)

# RN2107,RN2108,RN2109

Switching, Inverter Circuit, Interface Circuit and Driver Circuit Applications

- With built-in bias resistors
- Simplify circuit design
- Reduce a quantity of parts and manufacturing process
- Complementary to RN1107~RN1109

### **Equivalent Circuit and Bias Resister Values**



Type No.	R1 (kΩ)	R2 (kΩ)
RN2107	10	47
RN2108	22	47
RN2109	47	22

# 1. BASE 2. EMITTER 3. COLLECTOR 2.0.2 1.0.4.0.1 2.0.2 2.0.4.0.1 2.0.0.2 3. 0.0.4.2 3. 0.0.4.2 4.0.0.2 5.0.0.4.2 5.0.0.4.2 6.0.0.4.2 6.0.0.4.2 7.0.0.4.2 7.0.0.4.2 8.0.0.4.2 9.0.0.4.2 1. BASE 2. EMITTER 3. COLLECTOR

2-2H1A

Weight: 2.4mg

**TOSHIBA** 

### Maximum Ratings (Ta = 25°C) (Q1, Q2 Common)

Characteristic		Symbol	Rating	Unit	
Collector-base voltage	RN2107~RN2109	V <sub>CBO</sub>	-50	٧	
Collector-emitter voltage	KIN2 107 KIN2 109	V <sub>CEO</sub>	-50	V	
	RN2107		-6		
Emitter-base voltage	RN2108	V <sub>EBO</sub>	-7	V	
	RN2109		-15		
Collector current		IC	-100	mA	
Collector power dissipation	RN2107~RN2109		100	mW	
Junction temperature	RINZ 107~RINZ 109	Tj	150	°C	
Storage temperature range		T <sub>stg</sub>	-55~150	°C	

<sup>\*:</sup> Total rating





## Electrical Characteristics (Ta = 25°C) (Q1, Q2 Common)


Characteristic		Symbol	Test Circuit	Test Condition	Min	Тур.	Max	Unit
Collector cut-off current	RN2107	I <sub>CBO</sub>		$V_{CB} = -50V, I_{E} = 0$	_	_	-100	nA
	~RN2109		_	V <sub>CE</sub> = -50V, I <sub>B</sub> = 0	_	_	-500	nA
Emitter cut-off current	RN2107	I <sub>EBO</sub>	_	$V_{EB} = -6V, I_C = 0$	-0.081	_	-0.15	mA
	RN2108			$V_{EB} = -7V, I_C = 0$	-0.078	_	-0.145	
	RN2109			$V_{EB} = -15V, I_C = 0$	-0.167	_	-0.311	
	RN2107	h <sub>FE</sub>	_	V <sub>CE</sub> = -5V, I <sub>C</sub> = -10mA	80	_	_	_
DC current gain	RN2108				80	_	_	
	RN2109				70	_	_	
Collector-emitter saturation voltage	RN2107 ~RN2109	V <sub>CE</sub> (sat)	_	$I_C = -5$ mA, $I_B = -0.25$ mA	_	-0.1	-0.3	V
Input voltage (ON)	RN2107	V <sub>I (ON)</sub>	_	V <sub>CE</sub> = -0.2V, I <sub>C</sub> = -5mA	-0.7	_	-1.8	V
	RN2108				-1.0	_	-2.6	
	RN2109				-2.2	_	-5.8	
Input voltage (OFF)	RN2107	V <sub>I (OFF)</sub>	_	V <sub>CE</sub> = -5V, I <sub>C</sub> = -0.1mA	-0.5	_	-1.0	٧
	RN2108				-0.6	_	-1.16	
	RN2109				-1.5	_	-2.6	
Transition frequency	RN2107 ~RN2109	f <sub>T</sub>	_	V <sub>CE</sub> = -10V, I <sub>C</sub> = -5mA	_	200	_	MHz
Collector Output capacitance	RN2107 ~RN2109	C <sub>ob</sub>	_	V <sub>CB</sub> = -10V, I <sub>E</sub> = 0, f = 1MH <sub>z</sub>	_	3	6	pF
Input resistor	RN2107	R1	_	_	7	10	13	kΩ
	RN2108				15.4	22	28.6	
	RN2109				32.9	47	61.1	
Resistor ratio	RN2107				0.191	0.213	0.232	_
	RN2108	R1/R2	_		0.421	0.468	0.515	
	RN2109				1.92	2.14	2.35	


2


2001-06-07

















3







Type Name	Marking
RN2107	Type Name Y H
RN2108	Type Name Y I
RN2109	Type Name Y J

2001-06-07

5

### **RESTRICTIONS ON PRODUCT USE**

000707EAA

- TOSHIBA is continually working to improve the quality and reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to comply with the standards of safety in making a safe design for the entire system, and to avoid situations in which a malfunction or failure of such TOSHIBA products could cause loss of human life, bodily injury or damage to property.
  In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent TOSHIBA products specifications. Also, please keep in mind the precautions and conditions set forth in the "Handling Guide for Semiconductor Devices," or "TOSHIBA Semiconductor Reliability Handbook" etc..
- The TOSHIBA products listed in this document are intended for usage in general electronics applications (computer, personal equipment, office equipment, measuring equipment, industrial robotics, domestic appliances, etc.). These TOSHIBA products are neither intended nor warranted for usage in equipment that requires extraordinarily high quality and/or reliability or a malfunction or failure of which may cause loss of human life or bodily injury ("Unintended Usage"). Unintended Usage include atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, medical instruments, all types of safety devices, etc.. Unintended Usage of TOSHIBA products listed in this document shall be made at the customer's own risk.
- The information contained herein is presented only as a guide for the applications of our products. No
  responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other
  rights of the third parties which may result from its use. No license is granted by implication or otherwise under
  any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.