


Power Modules

Single Phase Diode Bridges

10-35 Amps

Part Number	U.S. Series	VRRM (V)	I _o T _c		VFM @ I _F (4)		I _{FSM} (1)	I _{FSM} (1)	R _{thJC} DC (2) (°C/W)	Case Outline Number (7)	Notes	Case Style
			(A)	(°C)	(V)	(A)	50 Hz (A)	60 Hz (A)				
	100JB05L 100JB1L 100JB2L 100JB4L 100JB6L 100JB8L 100JB10L 100JB12L	50 100 200 400 600 800 1000 1200	10	65	1.3	15.7	125	130	3.5		(3)	D-34A
26MB05A 26MB10A 26MB20A 26MB40A 26MB60A 26MB80A 26MB100A 26MB120A	250JB05L 250JB1L 250JB2L 250JB4L 250JB6L 250JB8L 250JB10L 250JB12L	50 100 200 400 600 800 1000 1200	25	65	1.1	55	335	350	1.8			
36MB05A 36MB10A 36MB20A 36MB40A 36MB60A 36MB80A 36MB100A 36MB120A	35MB05A 35MB10A 35MB20A 35MB40A 35MB60A 35MB80A 35MB100A 35MB120A	50 100 200 400 600 800 1000 1200	35	55	1.2	55	400	420	1.4			
26MB05B 26MB10B 26MB20B 26MB40B 26MB60B 26MB80B 26MB100B		50 100 200 400 600 800 1000	25	55	1.2	39	285	300	2.3		(6)	
36MB05B 36MB10B 36MB20B 36MB40B 36MB60B 36MB80B 36MB100B		50 100 200 400 600 800 1000	35	55	1.2	55	380	400	1.6			