4M High Speed SRAM (1-Mword \times 4-bit)

HITACHI

ADE-203-1202 (Z) Preliminary Rev. 0.0 Sep. 28, 2000

Description

The HM62W4100HC is a 4-Mbit high speed static RAM organized 1-Mword × 4-bit. It has realized high speed access time by employing CMOS process (6-transistor memory cell) and high speed circuit designing technology. It is most appropriate for the application which requires high speed and high density memory, such as cache and buffer memory in system. The HM62W4100HC is packaged in 400-mil 32-pin SOJ for high density surface mounting.

Features

• Single supply: $3.3 \text{ V} \pm 0.3 \text{ V}$

• Access time: 10 ns (max)

• Completely static memory

- No clock or timing strobe required
- Equal access and cycle times
- Directly TTL compatible
 - All inputs and outputs
- Operating current: 115 mA (max)
- TTL standby current: 40 mA (max)
- CMOS standby current: 5 mA (max)

: 1 mA (max) (L-version)

- Data retension current: 0.6 mA (max) (L-version)
- Data retension voltage: 2 V (min) (L-version)
- Center V_{CC} and V_{SS} type pinout


Preliminary: The specification of this device are subject to change without notice. Please contact your nearest Hitachi's Sales Dept. regarding specification.



Ordering Information

Type No.	Access time	Package
HM62W4100HCJP-10	10 ns	400-mil 32-pin plastic SOJ (CP-32DB)
HM62W4100HCLJP-10	10 ns	_


Pin Arrangement



Pin Description

Pin name	Function
A0 to A19	Address input
I/O1 to I/O4	Data input/output
CS	Chip select
ŌĒ	Output enable
WE	Write enable
V _{cc}	Power supply
V_{ss}	Ground
NC	No connection

Block Diagram



Operation Table

CS	OE	WE	Mode	V _{cc} current	I/O	Ref. cycle
Н	×	×	Standby	I _{SB} , I _{SB1}	High-Z	_
L	Н	Н	Output disable	I _{cc}	High-Z	_
L	L	Н	Read	I _{cc}	Dout	Read cycle (1) to (3)
L	Н	L	Write	I _{cc}	Din	Write cycle (1)
L	L	L	Write	I _{cc}	Din	Write cycle (2)

Note: ×: H or L

Absolute Maximum Ratings

Parameter	Symbol	Value	Unit
Supply voltage relative to V _{ss}	V _{cc}	-0.5 to +4.6	V
Voltage on any pin relative to V _{SS}	V _T	-0.5^{*1} to $V_{CC}+0.5^{*2}$	V
Power dissipation	P _T	1.0	W
Operating temperature	Topr	0 to +70	°C
Storage temperature	Tstg	-55 to +125	°C
Storage temperature under bias	Tbias	-10 to +85	°C

Notes: 1. V_{τ} (min) = -2.0 V for pulse width (under shoot) \leq 6 ns.

2. V_T (max) = V_{CC} + 2.0 V for pulse width (over shoot) \leq 6 ns.

Recommended DC Operating Conditions ($Ta = 0 \text{ to } +70^{\circ}C$)

Parameter	Symbol	Min	Тур	Max	Unit
Supply voltage	V _{cc} *3	3.0	3.3	3.6	V
	V _{SS} *4	0	0	0	V
Input voltage	V _{IH}	2.0	_	V _{CC} + 0.5*2	V
	V _{IL}	-0.5* ¹	_	0.8	V

Notes: 1. V_{IL} (min) = -2.0 V for pulse width (under shoot) \leq 6 ns.

- 2. V_{IH} (max) = V_{CC} + 2.0 V for pulse width (over shoot) \leq 6 ns.
- 3. The supply voltage with all $\rm V_{\rm cc}$ pins must be on the same level.
- 4. The supply voltage with all $V_{\rm SS}$ pins must be on the same level.

DC Characteristics (Ta = 0 to +70°C, V_{CC} = 3.3 V \pm 0.3 V, V_{SS} = 0V)

Parameter	Symbol	Min	Typ* ¹	Max	Unit	Test conditions
Input leakage current	II _{LI} I	_	_	2	μΑ	$Vin = V_{SS} to V_{CC}$
Output leakage current	II _{LO} I	_	_	2	μΑ	Vin = V _{ss} to V _{cc}
Operation power supply current	I _{cc}	_	_	115	mA	
Standby power supply current	I _{SB}	_	_	40	mA	Min cycle, $\overline{CS} = V_{IH}$, Other inputs = V_{IH}/V_{IL}
	I _{SB1}	_	TBD	5	mA	$ f = 0 \text{ MHz} \\ V_{\text{CC}} \ge \overline{\text{CS}} \ge V_{\text{CC}} - 0.2 \text{ V}, \\ (1) \ 0 \ V \le V \text{in} \le 0.2 \text{ V or} \\ (2) \ V_{\text{CC}} \ge V \text{in} \ge V_{\text{CC}} - 0.2 \text{ V} $
		*2	TBD*2	1*2		
Output voltage	V _{OL}	_	_	0.4	V	I _{OL} = 8 mA
	V _{OH}	2.4	_	_	V	$I_{OH} = -4 \text{ mA}$

Notes: 1. Typical values are at $V_{cc} = 3.3 \text{ V}$, $Ta = +25^{\circ}\text{C}$ and not guaranteed.

2. This characteristics is guaranteed only for L-version.

Capacitance (Ta = +25°C, f = 1.0 MHz)

Parameter	Symbol	Min	Тур	Max	Unit	Test conditions
Input capacitance*1	Cin	_	_	6	pF	Vin = 0 V
Input/output capacitance*1	C _{I/O}	_	_	8	pF	V _{I/O} = 0 V

Note: 1. This parameter is sampled and not 100% tested.

AC Characteristics (Ta = 0 to +70°C, V_{CC} = 3.3 V ± 0.3 V, unless otherwise noted.)


Test Conditions

• Input pulse levels: 3.0 V/0.0 V

• Input rise and fall time: 3 ns

• Input and output timing reference levels: 1.5 V

• Output load: See figures (Including scope and jig)



Read Cycle

		IIIVIOZVI	4100110		
		-10			
Parameter	Symbol	Min	Max	Unit	Notes
Read cycle time	t _{RC}	10	_	ns	
Address access time	t _{AA}	_	10	ns	
Chip select access time	t _{ACS}	_	10	ns	
Output enable to outpput valid	t _{OE}	_	5	ns	
Output hold from address change	t _{oH}	3	_	ns	
Chip select to output in low-Z	t _{CLZ}	3	_	ns	1
Output enable to output in low-Z	t _{oLZ}	0	_	ns	1
Chip deselect to output in high-Z	t _{CHZ}	_	5	ns	1
Output disable to output in high-Z	t _{OHZ}	_	5	ns	1

HM62W4100HC

Write Cycle

ШΛ	162 \	N/ A 1	nn	
П	VIOZI	/V4I	vu	пС


		-10			
Parameter	Symbol	Min Max		Unit	Notes
Write cycle time	t _{wc}	10	_	ns	
Address valid to end of write	t _{AW}	7	_	ns	
Chip select to end of write	t _{cw}	7	_	ns	9
Write pulse width	t _{WP}	7	_	ns	8
Address setup time	t _{AS}	0	_	ns	6
Write recovery time	t _{wR}	0	_	ns	7
Data to write time overlap	t _{DW}	5	_	ns	
Data hold from write time	t _{DH}	0	_	ns	
Write disable to output in low-Z	t _{ow}	3	_	ns	1
Output disable to output in high-Z	t _{OHZ}	_	5	ns	1
Write enable to output in high-Z	t _{wHZ}	_	5	ns	1

Note:


- 1. Transition is measured ±200 mV from steady voltage with Load (B). This parameter is sampled and not 100% tested.
- 2. Address should be valid prior to or coincident with $\overline{\text{CS}}$ transition low.
- 3. WE and/or CS must be high during address transition time.
- 4. if $\overline{\text{CS}}$ and $\overline{\text{OE}}$ are low during this period, I/O pins are in the output state. Then, the data input signals of opposite phase to the outputs must not be applied to them.
- 5. If the $\overline{\text{CS}}$ low transition occurs simultaneously with the $\overline{\text{WE}}$ low transition or after the $\overline{\text{WE}}$ transition, output remains a high impedance state.
- 6. t_{AS} is measured from the latest address transition to the later of \overline{CS} or \overline{WE} going low.
- 7. t_{WR} is measured from the earlier of \overline{CS} or \overline{WE} going high to the first address transition.
- 8. A write occurs during the overlap of a low \overline{CS} and a low \overline{WE} . A write begins at the latest transition among \overline{CS} going low and \overline{WE} going low. A write ends at the earliest transition among \overline{CS} going high and \overline{WE} going high. t_{WP} is measured from the beginning of write to the end of write.
- 9. t_{cw} is measured from the later of \overline{CS} going low to the end of write.

Timing Waveforms


Read Timing Waveform (1) $(\overline{WE} = V_{IH})$




Read Timing Waveform (2) $(\overline{WE}=V_{IH},\overline{CS}=V_{IL},\overline{OE}=V_{IL})$




Read Timing Waveform (3) $(\overline{WE}=V_{IH},\overline{CS}=V_{IL},\overline{OE}=V_{IL})^{*2}$



Write Timing Waveform (1) ($\overline{\text{WE}}$ Controlled)



Write Timing Waveform (2) $(\overline{CS} \text{ Controlled})$




Low V_{CC} **Data Retention Characteristics** ($Ta = 0 \text{ to } +70^{\circ}\text{C}$)

This characteristics is guaranteed only for L-version.

Parameter	Symbol	Min	Typ*1	Max	Unit	Test conditions
V _{cc} for data retention	V_{DR}	2.0	_	_	V	$V_{CC} \ge \overline{CS} \ge V_{CC} - 0.2 \text{ V}$ (1) $0 \text{ V} \le \text{Vin} \le 0.2 \text{ V}$ or (2) $V_{CC} \ge \text{Vin} \ge V_{CC} - 0.2 \text{ V}$
Data retention current	I _{CCDR}	_	TBD	600	μΑ	$V_{cc} = 3 \text{ V}, V_{cc} \ge \overline{\text{CS}} \ge V_{cc} - 0.2 \text{ V}$ (1) $0 \text{ V} \le \text{Vin} \le 0.2 \text{ V} \text{ or}$ (2) $V_{cc} \ge \text{Vin} \ge V_{cc} - 0.2 \text{ V}$
Chip deselect to data retention time	t _{CDR}	0	_	_	ns	See retention waveform
Operation recovery time	t _R	5	_	_	ms	_


Note: 1. Typical values are at $V_{cc} = 3.0 \text{ V}$, $Ta = +25^{\circ}\text{C}$, and not guaranteed.

Low \boldsymbol{V}_{CC} Data Retention Timing Waveform



Package Dimensions

HM62W4100HCJP/HCLJP Series (CP-32DB)



Cautions

- 1. Hitachi neither warrants nor grants licenses of any rights of Hitachi's or any third party's patent, copyright, trademark, or other intellectual property rights for information contained in this document. Hitachi bears no responsibility for problems that may arise with third party's rights, including intellectual property rights, in connection with use of the information contained in this document.
- 2. Products and product specifications may be subject to change without notice. Confirm that you have received the latest product standards or specifications before final design, purchase or use.
- 3. Hitachi makes every attempt to ensure that its products are of high quality and reliability. However, contact Hitachi's sales office before using the product in an application that demands especially high quality and reliability or where its failure or malfunction may directly threaten human life or cause risk of bodily injury, such as aerospace, aeronautics, nuclear power, combustion control, transportation, traffic, safety equipment or medical equipment for life support.
- 4. Design your application so that the product is used within the ranges guaranteed by Hitachi particularly for maximum rating, operating supply voltage range, heat radiation characteristics, installation conditions and other characteristics. Hitachi bears no responsibility for failure or damage when used beyond the guaranteed ranges. Even within the guaranteed ranges, consider normally foreseeable failure rates or failure modes in semiconductor devices and employ systemic measures such as fail-safes, so that the equipment incorporating Hitachi product does not cause bodily injury, fire or other consequential damage due to operation of the Hitachi product.
- 5. This product is not designed to be radiation resistant.
- 6. No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without written approval from Hitachi.
- 7. Contact Hitachi's sales office for any questions regarding this document or Hitachi semiconductor products.

HTACH

Semiconductor & Integrated Circuits. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Tel: Tokyo (03) 3270-2111 Fax: (03) 3270-5109

NorthAmerica : http://semiconductor.hitachi.com/ Europe http://www.hitachi-eu.com/hel/ecg Asia http://www.hitachi.com.sg/grp3/sicd Japan : http://www.hitachi.co.jp/Sicd/indx.htm

For further information write to:

Hitachi Semiconductor (America) Inc. 179 East Tasman Drive, San Jose, CA 95134 Tel: <1> (408) 433-1990 Germany

Hitachi Europe GmbH Electronic Components Group Dornacher Straße 3 D-85622 Feldkirchen, Munich

Fax: <1>(408) 433-0223 Tel: <49> (89) 9 9180-0 Fax: <49> (89) 9 29 30 00

Hitachi Europe Ltd. Electronic Components Group. Whitebrook Park Lower Cookham Road

Maidenhead Berkshire SL6 8YA, United Kingdom Tel: <886> (2) 2718-3666 Tel: <44> (1628) 585000 Fax: <44> (1628) 585160

Hitachi Asia Ltd. 16 Collyer Quay #20-00 Hitachi Tower Singapore 049318 Tel: 535-2100 Fax: 535-1533

Hitachi Asia Ltd. Taipei Branch Office 3rd Flr, Hung Kuo Building, No.167,

Tun Hwa North Road, Taipei (105) Taiwan

Fax: <886> (2) 2718-8180 Telex: 23222 HAS-TP

Copyright © Hitachi, Ltd., 2000. All rights reserved. Printed in Japan.

Hitachi Asia (Hong Kong) Ltd.

Kowloon, Hong Kong

Tel: <852> (2) 735 9218 Fax: <852> (2) 730 0281 Telex: 40815 HITEC HX

Group III (Electronic Components) 7th Fir, North Tower, World Finance Centre.

Harbour City, Canton Road, Tsim Sha Tsui,

Colophon 1.0