

Part Number : TDA11105PS

Function : Chip Assembly Using TV Circuit

Package : 64 Pin Type

Manufacturers : NXP Semiconductors.

Image :



Pinouts :

| | | | |
|----|----------|-----------|----|
| 1 | IFVO | CVBS4/Y4 | 64 |
| 2 | VP2 | AIN2/IN1L | 63 |
| 3 | VCCAUDIO | CVBS2/Y2 | 62 |
| 4 | PLLIF | AIN3/IN1R | 61 |
| 5 | GND2 | C2/C3/C4 | 60 |
| 6 | DECSDEM | LSL | 59 |
| 7 | FMDEMOUT | LSR | 58 |
| 8 | EHTO | FBISO | 57 |
| 9 | AGC | HOUT | 56 |
| 10 | IREF | GND3 | 55 |
| 11 | VSC | VP3 | 54 |
| 12 | IF IN2 | YSYNC | 53 |
| 13 | IF IN1 | YOUT | 52 |
| 14 | VDRA | PR/C3 | 51 |
| 15 | VDRB | Y3/CVBS | 50 |
| 16 | AVL/EW | PB | 49 |
| 17 | DECBG | BCLIN | 48 |
| 18 | SECPLL | BLKIN | 47 |
| 19 | GNG1 | ROUT | 46 |
| 20 | PHL1LF | GOUT | 46 |
| 21 | PHL2LF | BOUT | 44 |
| 22 | VP1 | VDDA | 43 |
| 23 | DECDIG | VPE | 42 |
| 24 | XTALOUT | GND5 | 41 |
| 25 | XTALIN | VDD | 40 |
| 26 | IR | | 39 |
| 27 | MUTE | STANDBY | 38 |
| 28 | TILT | TV/AV | 37 |
| 29 | KEY | | 36 |
| 30 | BAND2 | SCL | 35 |
| 31 | BAND1 | SDA | 34 |
| 32 | TUNING | VDDP | 33 |